



pITX-APL

Doc. Rev. 1.5

Doc-ID: 1061-1199

 PITX-APL – USER GUIDE

Disclaimer

Kontron would like to point out that the information contained in this manual may be subject to alteration, particularly as a result of the constant upgrading of Kontron products. This document does not entail any guarantee on the part of Kontron with respect to technical processes described in the manual or any product characteristics set out in the manual. Kontron assumes no responsibility or liability for the use of the described product(s), conveys no license or title under any patent, copyright or mask work rights to these products and makes no representations or warranties that these products are free from patent, copyright or mask work right infringement unless otherwise specified. Applications that are described in this manual are for illustration purposes only. Kontron makes no representation or warranty that such application will be suitable for the specified use without further testing or modification. Kontron expressly informs the user that this manual only contains a general description of processes and instructions which may not be applicable in every individual case. In cases of doubt, please contact Kontron.

This manual is protected by copyright. All rights are reserved by Kontron. No part of this document may be reproduced, transmitted, transcribed, stored in a retrieval system, or translated into any language or computer language, in any form or by any means (electronic, mechanical, photocopying, recording, or otherwise), without the express written permission of Kontron. Kontron points out that the information contained in this manual is constantly being updated in line with the technical alterations and improvements made by Kontron to the products and thus this manual only reflects the technical status of the products by Kontron at the time of publishing.

Brand and product names are trademarks or registered trademarks of their respective owners.

©2018 by Kontron S&T AG

Kontron S&T AG

Lise-Meitner-Str. 3-5

86156 Augsburg

Germany

www.kontron.com

Revision History

Revision	Brief Description of Changes	Date of Issue	Author
1.0	Initial Issue	2018-Mar-08	hjs
1.1	added information in chapter 5	2018-Jul-12	hjs
1.2	added chapter 6.17	2018-Jul-24	hjs
1.3	added note power plug	2018-Oct-01	hjs
1.4	added chapter 6.18 (Serial COM)	2018-Nov-13	hjs
1.5	added chapter 6.19 (Audio Connector)	2018-Dec-04	hjs

Intended Use

THIS DEVICE AND ASSOCIATED SOFTWARE ARE NOT DESIGNED, MANUFACTURED OR INTENDED FOR USE OR RESALE FOR THE OPERATION OF NUCLEAR FACILITIES, THE NAVIGATION, CONTROL OR COMMUNICATION SYSTEMS FOR AIRCRAFT OR OTHER TRANSPORTATION, AIR TRAFFIC CONTROL, LIFE SUPPORT OR LIFE SUSTAINING APPLICATIONS, WEAPONS SYSTEMS, OR ANY OTHER APPLICATION IN A HAZARDOUS ENVIRONMENT, OR REQUIRING FAIL-SAFE PERFORMANCE, OR IN WHICH THE FAILURE OF PRODUCTS COULD LEAD DIRECTLY TO DEATH, PERSONAL INJURY, OR SEVERE PHYSICAL OR ENVIRONMENTAL DAMAGE (COLLECTIVELY, "HIGH RISK APPLICATIONS").

You understand and agree that your use of Kontron devices as a component in High Risk Applications is entirely at your risk. To minimize the risks associated with your products and applications, you should provide adequate design and operating safeguards. You are solely responsible for compliance with all legal, regulatory, safety, and security related requirements concerning your products. You are responsible to ensure that your systems (and any Kontron hardware or software components incorporated in your systems) meet all applicable requirements. Unless otherwise stated in the product documentation, the Kontron device is not provided with error-tolerance capabilities and cannot therefore be deemed as being engineered, manufactured or setup to be compliant for implementation or for resale as device in High Risk Applications. All application and safety related information in this document (including application descriptions, suggested safety measures, suggested Kontron products, and other materials) is provided for reference only.

Customer Support

Find Kontron contacts by visiting: <http://www.kontron.com/support>.

Customer Service

As a trusted technology innovator and global solutions provider, Kontron extends its embedded market strengths into a services portfolio allowing companies to break the barriers of traditional product lifecycles. Proven product expertise coupled with collaborative and highly-experienced support enables Kontron to provide exceptional peace of mind to build and maintain successful products.

For more details on Kontron's service offerings such as: enhanced repair services, extended warranty, Kontron training academy, and more visit <http://www.kontron.com/support-and-services/services>.

Customer Comments

If you have any difficulties using this user guide, discover an error, or just want to provide some feedback, contact [Kontron support](#). Detail any errors you find. We will correct the errors or problems as soon as possible and post the revised user guide on our website.

Terms and Conditions

Kontron warrants products in accordance with defined regional warranty periods. For more information about warranty compliance and conformity, and the warranty period in your region, visit <http://www.kontron.com/terms-and-conditions>.

Kontron sells products worldwide and declares regional General Terms & Conditions of Sale, and Purchase Order Terms & Conditions. Visit <http://www.kontron.com/terms-and-conditions>.

For contact information, refer to the corporate offices contact information on the last page of this user guide or visit our website [CONTACT US](#).

Symbols

The following symbols may be used in this manual

⚠ DANGER

DANGER indicates a hazardous situation which, if not avoided, will result in death or serious injury.

⚠ WARNING

WARNING indicates a hazardous situation which, if not avoided, could result in death or serious injury.

⚠ CAUTION

CAUTION indicates a hazardous situation which, if not avoided, may result in minor or moderate injury.

NOTICE

NOTICE indicates a property damage message.



Electric Shock!

This symbol and title warn of hazards due to electrical shocks (> 60 V) when touching products or parts of them. Failure to observe the precautions indicated and/or prescribed by the law may endanger your life/health and/or result in damage to your material.

Please refer also to the "High-Voltage Safety Instructions" portion below in this section.



ESD Sensitive Device!

This symbol and title inform that the electronic boards and their components are sensitive to static electricity. Care must therefore be taken during all handling operations and inspections of this product in order to ensure product integrity at all times.



HOT Surface!

Do NOT touch! Allow to cool before servicing.



Laser!

This symbol inform of the risk of exposure to laser beam and light emitting devices (LEDs) from an electrical device. Eye protection per manufacturer notice shall review before servicing.



This symbol indicates general information about the product and the user manual.

This symbol also indicates detail information about the specific product configuration.



This symbol precedes helpful hints and tips for daily use.

Table of Contents

Symbols	6
Table of Contents	7
List of Tables.....	8
List of Figures	9
1/ Introduction.....	10
2/ Description.....	11
2.1. Configurations.....	12
2.2. Accessories List	12
3/ Installation procedure	14
3.1. Installing the Board	14
3.2. Requirements IEC60950-1.....	15
3.3. Lithium battery precautions	15
4/ System specifications	16
4.1. Component Main Data.....	16
5/ Jumpers and Connectors	21
5.1. Hardware Configuration Setting	21
5.1.1. Jumpers and Connectors.....	21
5.2. Mainboard Placement and Rear I/O locations.....	22
5.2.1. Rear Side.....	23
6/ Pin Definitions.....	25
6.1. Processor Support.....	26
6.2. System Memory Support.....	26
6.3. MicroSD and MicroSIM.....	27
6.4. Ethernet Connectors (I/O area).....	28
6.5. USB Connectors (I/O area)	29
6.6. Fan Connector (internal, J23)	31
6.7. DC Power Jack Connector (5 Vin Ext., J11).....	32
6.8. Internal Power Connector (Vin Int., J4)	33
6.9. Front Panel (FP) internal (J21).....	33
6.10. USB internal (J7, J8).....	34
6.11. SBC Connector (GPIO and Ext. Battery) (internal, J13)).....	34
6.12. Jumper Load BIOS Default and Clear CMOS (J15)	35
6.13. Jumper Always ON (J16).....	35
6.14. LVDS (internal, J19).....	36
6.15. SATA (Serial ATA) Disk Interfaces (internal, J9).....	37
6.16. Display Port	38
6.17. Slot Connector (mPCIe/mSATA) (J10)	39
6.18. Serial COM (J20).....	41
6.19. Front Panel Audio Connector (J22)	41
7/ uEFI BIOS.....	42
7.1. Starting the uEFI BIOS.....	42
7.2. Setup Menus.....	43
7.2.1. Main Setup Menu	43
7.2.2. Advanced Setup Menu.....	45
7.2.3. Chipset Setup Menu.....	50
7.2.4. Security Setup Menu	53
7.2.4.1. Remember the Password	54

7.2.5. Boot Setup Menu	55
7.2.6. Exit Setup Menu	57
7.3. The uEFI Shell.....	58
7.3.1. Basic Operation of the uEFI Shell.....	58
7.3.1.1. Entering the uEFI Shell.....	58
7.3.1.2. Exiting the uEFI Shell.....	58
7.4. uEFI Shell Scripting	59
7.4.1. Startup Scripting.....	59
7.4.2. Create a Startup Script.....	59
7.4.3. Examples of Startup Scripts.....	59
7.4.3.1. Execute Shell Script on other Harddrive.....	59
7.5. Firmware Update	59
7.5.1. Updating Procedure	59
List of Acronyms.....	61
About Kontron	62

List of Tables

Table 1: Component Main Data	12
Table 2: List of Accessories.....	12
Table 3: Component Main Data.....	16
Table 4: Environmental Conditions	19
Table 5: Connector Definitions.....	25
Table 6: Processor Support.....	26
Table 7: Memory Support	26
Table 8: Pin Assignment MicroSIM.....	27
Table 9: Pin Assignment MicroSD	27
Table 10: Pin Assignment.....	28
Table 11: Signal Description.....	29
Table 12: Pin Assignment	29
Table 13: Signal Description	29
Table 14: 3-pin Mode.....	31
Table 15: Signal Description	31
Table 16: Internal Power Connector	33
Table 17: FP Connection.....	33
Table 18: USB Internal Connection.....	34
Table 19: SPI Internal Connection.....	34
Table 20: CMOS Internal Connection	35
Table 21: Always ON Internal Connection	35
Table 22: LVDS Pin Assignment.....	36
Table 23: Pin Assignment	37
Table 24: Signal Description	37
Table 25: Display Port.....	38
Table 26: Pin Assignment mPCIe	39
Table 27: Pin Assignment Serial COM.....	41
Table 28: Pin Assignment Audio Connector	41
Table 29: Navigation Hot Keys Available in the Legend Bar.....	42
Table 30: Main Setup Menu Sub-screens	44
Table 31: Advanced Setup menu Sub-screens and Functions.....	46
Table 32: Chipset Setup menu Sub-screens and Functions.....	50
Table 33: Security Setup Menu Functions.....	53
Table 34: Boot Setup Menu Functions	55
Table 35: Save and Exit Setup Menu Functions.....	57

List of Figures

Figure 1: Premounted System with Battery Modul	12
Figure 2: Front Side and Interfaces.....	22
Figure 3: Rear Side.....	23
Figure 4: Battery Module	23
Figure 5: System parts with integrated premounted cooler.....	24
Figure 6: Combo Connector for MicroSD and MicroSIM	27
Figure 7: Ethernet Connector	28
Figure 8: USB 2.0/3.0 socket.....	29
Figure 9: USB 2.0 High Speed Cable.....	30
Figure 10: USB 3.0 High Speed Cable.....	30
Figure 11: 3-pin Fan Connector	31
Figure 12: Power Jack Connector	32
Figure 13: Internal Power Connector.....	33
Figure 14: FP Connector	33
Figure 15: USB Internal Connector	34
Figure 16: SBC Connector	34
Figure 17: CMOS Internal Connector	35
Figure 18: Always ON.....	35
Figure 19: LVDS Connector.....	36
Figure 20: SATA Connector.....	37
Figure 21: Available Cable Kit.....	37
Figure 22: Display Port.....	38
Figure 23: Slot Connector (mPCIe).....	39
Figure 24: Serial COM	41
Figure 25: Audio Connector	41
Figure 26: Main Setup Menu Initial Screen.....	43
Figure 27: Advanced Setup Menu Initial Screen	45
Figure 28: Chipset Setup Menu Initial Screen	50
Figure 29: Security Setup Menu Initial Screen	53
Figure 30: Boot Setup Menu Initial Screen.....	55
Figure 31: Save and Exit Setup Menu Initial Screen.....	57

1/ Introduction

This manual describes the pico-ITX board with Intel CPU. This board will also be denoted pITX-APL within this Users Guide.

The use of this Users Guide implies a basic knowledge of PC hard- and software. This manual is focussed on describing the pITX-APL board's special features and is not intended to be a standard PC textbook.

New users are recommended to study the short installation procedure stated in the following chapter before switching-on the power.

All configuration and setup of the CPU board is either done automatically or manually by the user via the BIOS setup menus.

Latest revision of this manual, datasheet, BIOS, drivers, BSPs (Board Support Packages) can be downloaded from Kontron Web Page.

2/ Description

The board is based on the Intel System on Chip (SoC) and is mechanically compliant to the Pico-ITX (pITX) specification. Board key features are:

- ▶ one 204-pin DDR3L 1333/1600/1866MHz SO-DIMM non-ECC socket (up to 8GB)
- ▶ one Display Port Rear Connector
- ▶ one 24-bit Dual-Channel LVDS Converter for External Display with 5 V Backlight
- ▶ one 10/100/1000 Gigabit LAN Rear Port
- ▶ one Dual-Stacked USB 3.0 Rear Port
- ▶ one mPCIe/mSATA half-size connector with SIM Card Interface and USB 2.0
- ▶ one SATA Gen3 (up to 6 GB/s) connector
- ▶ one 4-wire RS-232 Serial Port internal header
- ▶ one Internal SPI Interface for external device
- ▶ HD Audio with microphone, Stereo Line-in & Stereo Line-out internal header
- ▶ one Internal Front Panel Header for LEDs, Power Buttons and PC Speaker
- ▶ Security: WIBU Secure Element and TPM 2.0
- ▶ one Internal Header for up to eight configurable GPIOs
- ▶ Temperature Sensor and cooling solution
- ▶ two USB 2.0 internal headers
- ▶ one microSD card slot

Built with these functions, pITX-APL Mother Board is ideal for ATM, Automation, Kiosk applications, medical equipment, industrial automation, financial automation, process control, semiconductor equipment and network security markets.

2.1. Configurations

Kontron offers the pITX-APL in different configurations. The products can be ordered in four different flavors.

Table 1: Component Main Data

Product Number	Description	MTBF (hours)
44010-0000-23-2	Intel® Mobile Celeron® N3350 2C 2.3 GHz, 6W, Commercial temp, Entry	1,571,585
44010-0000-20-4	Intel® Atom™ x7 E3950 4C 2.0 GHz, 13W, Industrial temp, High	1,577,287
44010-0000-18-4	Intel® Atom™ x5 E3940 4C 1.8 GHz, 9,5W, Industrial temp, Intermediate	1,577,287
44010-0000-18-2	Intel® Atom™ x5 E3930 2C 1.8 GHz, 6,5W, Industrial temp, Entry	1,577,287

⚠ WARNING

Warning: If changing the premounted cooling system, then the system might get overheated resulting in instable system or defects if the cooling system is insufficient.

Figure 1: Premounted System with Battery Modul



2.2. Accessories List

Table 2: List of Accessories

Connector (RefDes)	On-Board Connectors		Mating Connectors/Cables	
	Manufacturer	Part No.	Manufacturer	Part No.
Fan (J23)	Molex	53047-0310	Molex	51021-0300
			Kontron	1060-9200
SATA (J9)	Lotes	ABA-SAT-010-K08	Kontron	96079-0000-00-1
Audio (J22)	Molex	53261-0671	Molex	51021-0600
			Kontron	96063-0000-00-1
DC Jack (J11)	Kycon	KLDHCX-0202-A-LT	Kycon	KLDX-PA-0202-A-LT
Internal Power (J4)	Leoco	2521P04VW00	Leoco	2520S040000

Connector (RefDes)	On-Board Connectors		Mating Connectors/Cables	
	Manufacturer	Part No.	Manufacturer	Part No.
LVDS (J19)	Samtec	SHF-120-01-F-D-SM-K-TR	Don Connex	A32-40-C-G-B-1
	Pinrex	53C-90-40GBE0	Pinrex	977-31-403204
			Kontron	821515
Serial COM (J20)	Molex	53261-0571	Molex	51021-0500
			Kontron	1055-8059
SPI (J12)	Molex	53261-0971	Molex	51021-0900
GPIO (Battery Module)	Molex	53261-1071	Molex	51021-1000
			Kontron	1055-8063
GPIO/RTC (J13)	Molex	87758-1216	Molex	79107-7205
			Kontron	1055-7645
Front Panel (J21)	Molex	87759-1014	Molex	51110-1050
	Amphenol-FCI	57202-F52-06LF	Kontron	1055-8065
USB2.0 (J7, J8)	Molex	53047-0410	Molex	51021-0400
			Kontron	96054-0000-00-2

3/ Installation procedure

3.1. Installing the Board



ESD Sensitive Device!

Electrostatic discharge (ESD) can damage equipment and impair electrical circuitry.

- Wear ESD-protective clothing and shoes
- Wear an ESD-preventive wrist strap attached to a good earth ground
- Check the resistance value of the wrist strap periodically (OK: 1 MΩ to 10 MΩ)
- Transport and store the board in its antistatic bag
- Handle the board at an approved ESD workstation
- Handle the board only by the edges

To get the board running follow these steps. If the board shipped from Kontron has already components like RAM and CPU cooler mounted, then relevant steps below can be skipped.

1. Turn off the PSU (Power Supply Unit)

NOTICE

Turn off PSU (Power Supply Unit) completely (no mains power connected to the PSU) or leave the Power Connectors unconnected while configuring the board. Otherwise components (RAM, LAN cards etc.) might get damaged. Make sure to use +5V single supply only. Alternatively use a standard ATX PSU with suitable cable kit and PS_ON# active.

2. Insert the memory module

Be careful to push it in the slot(s) before locking the tabs. For a list of approved memory modules contact your Distributor or FAE. See also chapter "System Memory Support". Use memory modules with the same density in all sockets!

3. Cooler Installation

Normally the cooler is premounted, but in case not, then make sure that the heat paste etc. on the cooler is intact and cover the full area of the SoC. Connect cooler fan electrically to the FAN_CPU connector.

4. Connecting Interfaces

Insert all external cables for hard disk, keyboard etc. A monitor must be connected in order to change BIOS settings.

5. Connect and turn on PSU

Connect PSU to the board by the ATX+5 V-4pin connector or alternatively connect an external 5 V DC power adapter to the rear DC jack.

6. BIOS Setup

Enter the BIOS setup by pressing the key during boot up.

Enter "Exit Menu" and load Setup Defaults.

Refer to the "BIOS Configuration / Setup" section of this manual for details on BIOS setup.



To clear all BIOS settings, including Password protection, activate "Load Default BIOS Settings" Jumper for > 10 sec (without power connected).

7. Mounting the board in chassis

NOTICE

When mounting the board to chassis etc. please notice that the board contains components on both sides of the PCB which can easily be damaged if board is handled without reasonable care. A damaged component can result in malfunction or no function at all.

When fixing the Motherboard on a chassis it is recommended to use screws with integrated washer and a diameter of > 7 mm. Do not use washers with teeth, as they can damage the PCB and cause short circuits.

3.2. Requirements IEC60950-1

Take care when designing chassis interface connectors in order to fulfil the IEC60950-1 standard. Users of pITX-APL must evaluate the end product to ensure compliance the requirements of the IEC60950-1 safety standard are met:

- ▶ The motherboard must be installed in a suitable mechanical, electrical and fire enclosure.
- ▶ The system in its enclosure must be evaluated for temperature and air flow considerations.
- ▶ The motherboard must be powered by a CSA or UL approved power supply that limits the maximum input current to 6 A to an external 5 V locking barrel-type DC jack or to an internal 5 V 4-pin DC power connector.
- ▶ For interfaces having a power pin such as external power or fan, ensure that the connectors and wires are suitably rated. All connections from/to the product shall be with SELV circuits only.
- ▶ Wires have suitable rating to withstand the maximum available power.
- ▶ The enclosure of the peripheral device fulfils the fire protecting requirements of IEC60950-1.

3.3. Lithium battery precautions

CAUTION

Danger of explosion if the lithium battery is incorrectly replaced.

- Replace only with the same or equivalent type recommended by the manufacturer
- Dispose of used batteries according to the manufacturer's instructions

VORSICHT! Explosionsgefahr bei unsachgemäßem Austausch der Batterie.

- Ersatz nur durch denselben oder einen vom Hersteller empfohlenen Typ
- Entsorgung gebrauchter Batterien nach Angaben des Herstellers

ATTENTION! Risque d'explosion avec l'échange inadéquat de la batterie.

- Remplacement seulement par le même ou un type équivalent recommandé par le producteur
- L'évacuation des batteries usagées conformément à des indications du fabricant

PRECAUCION! Peligro de explosión si la batería se sustituye incorrectamente.

- Sustituya solamente por el mismo o tipo equivalente recomendado por el fabricante
- Disponga las baterías usadas según las instrucciones del fabricante

ADVARSEL! Lithiumbatteri – Eksplosionsfare ved fejlagtig håndtering.

- Udskiftning må kun ske med batteri af samme fabrikat og type
- Levér det brugte batteri tilbage til leverandøren.

ADVARSEL! Eksplosjonsfare ved feilaktig skifte av batteri.

- Benytt samme batteritype eller en tilsvarende type anbefalt av apparatfabrikanten.
- Brukte batterier kasseres i henhold til fabrikantens instruksjoner

VARNING! Explosionsfara vid felaktigt batteribyte.

- Använd samma batterityp eller en ekvivalent typ som rekommenderas av apparattillverkaren.
- Kassera använt batteri enligt fabrikantens instruktion.

VAROITUS! Paristo voi räjähtää, jos se on virheellisesti asennettu.

- Vaihda paristo ainoastaan laitevalmistajan suosittelemaan tyyppiin
- Hävitä käytetty paristo valmistajan ohjeiden mukaisesti

4/ System specifications

4.1. Component Main Data

The table below summarizes the features of the pITX-APL embedded motherboard.

Table 3: Component Main Data

Motherboard pITX-APL	
Form factor	Pico-ITX (100 mm by 72 mm by 1.6 mm/Length x Width x Thickness)
Mechanical Dimensions with cooling	100 mm x 72 mm x 41 mm (Length x Width x Height)
Processor	Onboard CPU variants Intel® Processor line, 14 nm SoC ▶ Intel® Atom™ x7 E3950 4C 2.0 GHz, 13 W ▶ Intel® Atom™ x5 E3940 4C 1.8 GHz, 9.5 W ▶ Intel® Atom™ x5 E3930 2C 1.8 GHz, 6.5 W ▶ Intel® Mobile Celeron® N3350 2C 2.3 GHz, 6 W
BIOS	Winbond W25Q128FV5IG or Micron N25Q128A13E5E40F (128Mb) for System BIOS
EEPROM	Atmel AT24C32 for board information
Memory	one DDR3L non-ECC SODIMM 1333/1600/1866 MHz, single-channel ▶ DDR3L memory interface (up to 8 GB)
Flash Memory	The pITX-APL board supports microSD cards via onboard microSD/microSIM combo connector. The microSD card interface is sharing a combo connector with the micro SIM card.
Storage	The pITX-APL supports one SATA Gen 3 port.
Wake On	Wake on LAN, USB, Power button (S3 to S5)
Hardware Status Monitor	The hardware monitoring chip NCT7802Y is connected via SMBus and incorporates the following features: ▶ CPU Temperature Monitoring ▶ Voltages Level ▶ Fan Control
TPM	Infineon SLB9665XQ2.0
Power management	ACPI 5.0 support: ▶ Processor Core C-States (CC0, CC1, CC6) ▶ Processor Core/Package States support (C0, C1, C1E, C6, C6L, C7, C8, C9, C10) ▶ Processor Module States (MC0-CC0, MC0-CC6, MC7) ▶ Display States support (D0, D1, D2, D3, D4, D5, D9) ▶ Graphics States (RC0, RC1, RC6) ▶ System Sleep States (S0, S0ix, S3, S4, S5) ▶ Dynamic I/O power reduction (disabling sense amps on input buffers, tri-stating output buffers) ▶ Active power-down of Display links
Battery	BR2032 See Safety Instructions below this table!
Expansion	1x mPCIe (PCIe Rev 2.0) / mSATA (SATA Gen 3.0) with USB 2.0 and microSIM interface

Operating System Support	Six different Board Support Packages are offered: ▶ BSP1: Windows 10 IOT Enterprise 64 bit, eMMC Boot ▶ BSP2: Windows 10 IOT Core, Redstone 64 bit ▶ BSP3: Windows 7, 64 bit, eMMC boot (optional) ▶ BSP4: Windows ES 7, 64 bit, eMMC boot (optional) ▶ BSP5: Linux 64 bit, Yocto ▶ BSP6: VxWorks 7.x or newer (optional) ▶ API: KEAPI 3 for all OS (except for VxWorks)
External I/O	
LAN, USB3.0	one RJ-45 LAN Ports and dual USB3.0
Display Port (DP)	one Display Port connector Version 1.2
Power	5 V DC-IN Power Jack
Internal I/O	
SATA	one SATA Gen 3 Straight with Locking Latch
USB	two USB 2.0 4-pin header
Serial Peripheral Interface (SPI)	internal 9-pin header
LVDS	one (2 x 20-pin) pin-header
Mini PCIe	one mPCIe/mSATA (Half-size)
Audio	Internal header for Line-Out , Line-In and Microphone
Serial	one RS232
Internal Header	
Power	one Locking barrel-type DC Power Jack one internal 4-pin Power connector one 1 x 3-pin power connector for CPU Fan
CMOS Clear/Autostart	two (1 x 3) 2 mm pin-header
Front Panel	one 2 x 5-pin connector
MicroSD/microSIM	one microSD & microSIM combo socket adapter

Display	
Graphics Controller	The pITX-APL board onboard graphics support two simultaneous displays via two Digital Display Interface (DDI) and one eDP output. First DDI output is connected directly to a rear DisplayPort connector. Second DDI is unused. eDP output is converted to LVDS by NXP PTN3460BS DisplayPort to dual-channel 24-bit LVDS converter. The LVDS interface is provided on a standard 40-pin connector.
eDP to LVDS Controller	NXP PTN3460BS
Display Interface	one Display Port and LVDS internal Note: Two independent Displays Max.
Resolution	DP/LVDS 4096x2304 @ 60 Hz, 24 bpp (One panel display)
Ethernet	
Controller	Intel i210/i211
Interface	IEEE 802.3 10BASE-T / 100BASE-TX / 1000BASE-T compliant
Audio	
Universal Audio Architecture (UAA)	The onboard audio codec supports High Definition Audio with UAA (Universal Audio Architecture). The following connections are available via an internal header: ▶ Stereo Line-Out ▶ Stereo Line-in ▶ Mono Microphone-in
Power	
External Power Supply	The pITX-APL is operated by a single 5 V DC supply via a locking Barrel-type jack or through an internal 4-pin header.

Danger of explosion if the lithium battery is incorrectly replaced.
⚠ CAUTION

- Replace only with the same or equivalent type recommended by the manufacturer
 - Dispose of used batteries according to the manufacturer's instructions
-

Table 4: Environmental Conditions

Operating	It is the customer's responsibility to provide sufficient airflow around each of the components to keep them within allowed temperature range. The board has two temperature ranges: ▶ commercial grade: 0°C to +60°C (32°F~140°F) operating temperature (forced cooling). ▶ extended grade: -25°C to +75°C (-13°F~167°F) operating temperature (SKU Dependent and with standard cooler running at maximum speed) ▶ DC Voltage Limits: $\pm 7\%$ % of nominal voltage. 10 % to 95 % relative humidity non-condensing at temperature of 25°C to 30°C
Storage	-40°C to 85°C (-40°F to 185°F); lower limit of storage temperature is defined by specification restriction of on-board BR2032 battery. Up to 95 % relative humidity (temperature 25°C to 30°C) ▶ Thermal ramps: 4 cycles between limits at a rate of $\leq 20^\circ\text{C}$ per hour ▶ Temperature extremes: 36 nonconsecutive hours at high limit ▶ 24 nonconsecutive hours at low limit
Radiated Emissions (EMI)	All Peripheral interfaces intended for connection to external equipment are EMI protected. Compliant to the requirements of: ▶ EN55022 Class B radiated and conducted ▶ EN 61000-6-4:2007 (EMC) Generic emission standard Part 6-4: Emission standard for industrial environments ▶ EN 61000-6-2:2005 (EMC) – Generic standard – Immunity for industrial environmental
Immunity	Includes following tests accordingly: ▶ IEC 61000 PT4-2, (EN 61000-4-2) Electrostatic discharge immunity ESD ▶ IEC 61000 PT4-3, (EN 61000-4-3 and ENV 50204) Radiated Field ▶ IEC 61000 PT4-4, (EN 61000-4-4) Electrical fast transient/burst (EFT) BURST ▶ IEC 61000 PT4-5, (EN 61000-4-5) Surge immunity test ▶ IEC 61000 PT4-6, (EN 61000-4-6) Immunity to conducted disturbances ▶ IEC 61000 PT4-8, (EN 61000-4-8) Immunity to magnetic fields (LOW) ▶ IEC 61000 PT4-11, (EN 61000-4-11) Testing and measuring techniques-voltage dips, short interruption, and voltage variations immunity tests
Safety	EN 60950-1:2006 +A11:2009 +A1:2010 +A12:2011: Safety for information technology equipment including electrical business equipment
Shock	Conducted in standard available ATX chassis. Test is following Standard IEC 60068-2-27, half-sine wave, Acceleration 2 g, Pulse duration : 11 ms. Number of shocks: 600 shocks (100 shocks for each face.)
Bump	IEC 60068-2-27: Half Sine Waveform Acceleration 2 g; Pulse Duration 11 ms. Number of shocks: 600 shocks (100 shocks for each face.)
Vibration	AW IEC 60068-2-64, test Fh, Random Vibration, 90 min per axis, 3 axes at 1.9 grms, with PSD: 10-20Hz: 0.05 g²/Hz and 20-500Hz:- 3dB/octave.
MTBF	1,571,585 to 1,577,287 hours depending on processor type and according to Telcordia standard SR-332 Issue 3 at 30°C
Restriction of Hazardous Substances (RoHS II)	The product will comply to the European Council Directive on the approximation of the laws of the member states relating to Directive 2001/65/EU or the last status thereof.
Altitude	2000 m max., optionally 3000 m

Cooler	The Cooler heatspreader is active on the mITX-APL, so the cooler has integrated fan (UL-approved) with the following specifications: Supply Voltage: 4.5 V to 5.5 V Startup Voltage: 4.0 V Rotation Speed, rated: 5000 RPM Noise level, maximum: 27.0 dB(A) MTBF: 70000 Hours @ 40°C Operating Temperature: -25°C to +90°C
---------------	---

5/ Jumpers and Connectors

5.1. Hardware Configuration Setting

This chapter gives the definitions and shows the positions of jumpers, headers and connectors. All of the configuration jumpers on the board are in the proper position. The default settings shipped from factory are marked with an asterisk (*).


In general, jumpers on the board are used to select options for certain features. Some of the jumpers are designed to be user-configurable, allowing for system enhancement. The others are for testing purpose only and should not be altered. To select any option, cover the jumper cap over (SHORT) or remove (NC) it from the jumper pins according to the following instructions. Here, NC stands for "Not Connect".

5.1.1. Jumpers and Connectors

Jumper	Function	Remark
CLR_CMOS (J15)	Clear CMOS	1 x 3 header
AUTOSTART (J16)	Always on	1 x 3 header
Connector	Function	Remark
CPU_FAN1 (J23)	CPU FAN Connector	1 x 3 wafer
FP (J21)	Front Panel Connector	2 x 5 header
LVDS (J27)	LVDS Connector	2 x 20 connector
ATX 4-pin (J4)	ATX Power Connector	1 x 4 connector
DC Jack (J11)	Power Connector	Jack
MINI-PCIE (J29)	Mini PCIe Connector	2 x 26 connector
SATA	SATA3.0 Connector	Standard
BAT	Battery Socket	BR2032 compatible
SODIMM	Memory Socket	Slot
GPIO (J13)	GPIO connector	1 x 10 wafer
USB 2.0 internal	USB internal	2x 4-pin connector
Front Panel Audio (J22)	Audio connector	1x 6-pin Header

5.2. Mainboard Placement and Rear I/O locations


Figure 2: Front Side and Interfaces



- | | |
|---|---|
| 1 CPU | 11 SBC Connector (eight GPIOs and RTC battery via SBC Battery Module) (J13) |
| 2 Front Panel header (J21) | 12 Power connector (J4) |
| 3 Load BIOS Default Jumper (right)
Autostart Jumper (left) | 13 DC Power Jack (J11) |
| 4 CPU fan (J23) | 14 Dual USB 3.0 |
| 5 LVDS connector (J19) | 15 Ethernet |
| 6 RS232 connector (J20) | 16 Display Port |
| 7 mPCIe/mSATA connector | |
| 8 2x USB 2.0 connector | |
| 9 SATA connector (J9) | |
| 10 Four-Pin Power connector (J4) | |


5.2.1. Rear Side

Figure 3: Rear Side




- 17 MicroSIM/MicroSD Combo adapter
- 18 Memory slot
- 19 Front Panel Audio connector (J22)
- 20 BIOS recovery (J12)

Figure 4: Battery Module



- 21 SBC Header to board
- 22 GPIO Header

Figure 5: System parts with integrated premounted cooler



6/ Pin Definitions

The following sections provide pin definitions and detailed description of all on-board connectors.
The connector definitions follow the following notation:

Table 5: Connector Definitions

Column Name	Description
Pin	Shows the pin-numbers in the connector. The graphical layout of the connector definition tables is made similar to the physical connectors.
Signal	The mnemonic name of the signal at the current pin. The notation "XX#" states that the signal "XX" is active low.
Type	AI: Analog Input. AO: Analog Output. I: Input, TTL compatible if nothing else stated. IO: Input / Output. TTL compatible if nothing else stated. IOT: Bi-directional tristate IO pin. IS: Schmitt-trigger input, TTL compatible. IOC: Input / open-collector Output, TTL compatible. IOD: Input / Output, CMOS level Schmitt-triggered. (Open drain output) NC: Pin not connected. O: Output, TTL compatible. OC: Output, open-collector or open-drain, TTL compatible. OT: Output with tri-state capability, TTL compatible. LVDS: Low Voltage Differential Signal. PWR: Power supply or ground reference pins.
	Ioh: Typical current in mA flowing out of an output pin through a grounded load, while the output voltage is > 2.4 V DC (if nothing else stated). Iol: Typical current in mA flowing into an output pin from a VCC connected load, while the output voltage is < 0.4 V DC (if nothing else stated).
Pull U/D	On-board pull-up or pull-down resistors on input pins or open-collector output pins.
Note	Special remarks concerning the signal.
Designation	Type and number of item described
see Section	Number of section in this manual containing detailed description

6.1. Processor Support

The Intel BGA1296 14 nm is a SoC architecture with integrated Memory and Graphics Controller. The system supports the following embedded Stockkeeping Units (SKUs):

- ▶ Intel® Atom™ x7 E3950 4C 2.0 GHz, 12 W
- ▶ Intel® Atom™ x5 E3940 4C 1.8 GHz, 9.5 W
- ▶ Intel® Atom™ x5 E3930 2C 1.8 GHz, 6.5 W
- ▶ Intel® Mobile Celeron® N3350 2C 2.3 GHz, 6 W

Kontron has defined the board versions as listed in the following table, so far all based on Embedded CPUs.

Table 6: Processor Support

Name	Product number	Speed	Embed.	Cache	TDP / Tj
Atom x7 E3950 4C	44010-0000-20-4	2.0 GHz	Yes	2 MB	12 W/110°C
Atom x5 E3940 4C	44010-0000-18-4	1.8 GHz	Yes	2 MB	9.5 W/85°C
Atom x5 E3930 4C	44010-0000-18-2	1.8 GHz	Yes	2 MB	6.5 W/110°C
Mobile Celeron N3350 2C	44010-0000-23-2	2.3 GHz	Yes	2 MB	6 W/105°C

6.2. System Memory Support

The pITX-APL board supports a single-channel non-ECC DDR3L memory interface with one SODIMM. The integrated memory controller can support memory speeds of 1333/1600/1867 MHz. Maximum memory supported is 8 GB.

- ▶ DDR3L, 8 GB 1867MHz, PC3-1867, non-ECC SODIMM



If using 32 Bit OS, less than 4 GB are displayed in the system (Shared Video Memory/PCI resources are subtracted).

Kontron offers the following memory module:

Table 7: Memory Support

Memory Module Description
DDR3L, 8 GB 1867 MHz, PC3-1867

6.3. MicroSD and MicroSIM

Figure 6: Combo Connector for MicroSD and MicroSIM




Table 8: Pin Assignment MicroSIM

Pin	Type
1	V_VCC
2	RST
3	CLK_S3
4	RSVD_S4
5	GND_S5
6	V_VPP
7	I/O
8	RSVD_S8

Table 9: Pin Assignment MicroSD

Pin	Type
1	DAT2
2	CD/DAT3
3	CMD
4	V_VDD
5	CLK_T5
6	VSS/GND
7	DAT0
8	DAT8
SW	CARD_DETECT

6.4. Ethernet Connectors (I/O area)

The pITX-APL supports three channels of 10/100/1000 Mbit/s Ethernet (LAN1 to LAN3).

In order to achieve the specified performance of the Ethernet port, Category 5 twisted pair cables must be used with 10/100 MByte/s and Category 5E, 6 or 6E with 1 Gbit/s LAN networks.

Figure 7: Ethernet Connector




Table 10: Pin Assignment

Pin	Signal	Ethernet 10 BaseT/100BaseT	Gigabit-Ethernet
1	MDI0+	TX+	D1+
2	MDI0-	TX-	D1-
3	MDI1+	RX+	D2+
4	MDI1-		D3+
5	MDI2+		D3-
6	MDI2-	RX-	D2-
7	MDI3+		D4+
8	MDI3-		D4-

Table 11: Signal Description

Signal	Description
MDI[0]+ / MDI[0]-	In MDI mode, this is the first pair in 1000Base-T, i.e. the BI_DA+/- pair, and is the transmit pair in 10Base-T and 100Base-TX. In MDI crossover mode, this pair acts as the BI_DB+/- pair, and is the receive pair in 10Base-T and 100Base-TX.
MDI[1]+ / MDI[1]-	In MDI mode, this is the second pair in 1000Base-T, i.e. the BI_DB+/- pair, and is the receive pair in 10Base-T and 100Base-TX. In MDI crossover mode, this pair acts as the BI_DA+/- pair, and is the transmit pair in 10Base-T and 100Base-TX.
MDI[2]+ / MDI[2]-	In MDI mode, this is the third pair in 1000Base-T, i.e. the BI_DC+/- pair. In MDI crossover mode, this pair acts as the BI_DD+/- pair.
MDI[3]+ / MDI[3]-	In MDI mode, this is the fourth pair in 1000Base-T, i.e. the BI_DD+/- pair. In MDI crossover mode, this pair acts as the BI_DC+/- pair.

6.5. USB Connectors (I/O area)

The pITX-APL board contains support for two USB3.0/2.0 in the IO area. Two internal USB2.0 ports are available via internal 4-pin connectors. USB 2.0 ports allowing data transfers up to 480 Mb/s. The USB 3.0 port allowing data transfers up to 5 Gb/s.

Figure 8: USB 2.0/3.0 socket




Table 12: Pin Assignment

Pin	Type	Signal	Note
1	PWR	GND	USB2.0 / 3.0
2	IO	USB n+	USB2.0 / 3.0
3	IO	USB n-	USB2.0 / 3.0
4	PWR	5 V / SB 5 V	USB2.0 / 3.0
5	IO	TXn+	USB3.0
6	IO	TXn-	USB3.0
7	PWR	GND	USB3.0
8	IO	RXn+	USB3.0
9	IO	RXn-	USB3.0


Table 13: Signal Description

Signal	Description
USBn+ USBn-	Differential pair works as serial differential receive/transmit data lines.

Signal	Description
RXn+ RXn- TXn+ TXn-	Change to: USB2.0 (n=0,1,2,3), USB3.0 (n=0,1)
5 V / SB5 V	5 V supply for external devices. SB5 V is supplied during power-down to allow wakeup on USB device activity. Protected by a 2A current limiting IC (1A for each port).


For USB2.0 cabling it is required to use only HiSpeed USB cable, specified in USB2.0 standard:

Figure 9: USB 2.0 High Speed Cable



For USB3.0 cabling it is required to use only HiSpeed USB cable, specified in USB3.0 standard:

Figure 10: USB 3.0 High Speed Cable



6.6. Fan Connector (internal, J23)

The Fan can be used to actively cool the heatsink mounted on the board. The fan rotation speed can be monitored and the fan speed controlled by the temperature of the PCB (near SoC).

Figure 11: 3-pin Fan Connector




Table 14: 3-pin Mode


Pin	Signal	Description	Type
1	TACHO	Rotation speed	I
2	PWM	PWM output	0-5V
3	GND	Ground	PWR

Table 15: Signal Description

Signal	Description
GND	Power Supply GND signal
TACHO	Tacho input signal from the fan, for rotation speed supervision RPM (Rotations Per Minute).
PWM	Output signal for FAN speed control.

6.7. DC Power Jack Connector (5 Vin Ext., J11)

Figure 12: Power Jack Connector



Either the DC Power Jack Connector (5 Vin Ext.) or the "5 Vin Int." connector must be used to supply the board with +5V +/-5 %.

The 5 Vin Ext. power connector has Vin to the center pin and mates with Ø 6.3 mm DC Power jack with Ø 2.0 mm pin hole. (DC Connector RA 2 mm locking type). Maximum allowed current is 5 A.

⚠ CAUTION

The board can be supplied via the AC/DC adapter plugged into the power jack. Such adapters have usually no connection to protective earth. Consequently, the potential of the conductive parts on the board may drift. If a human touches such a part, this may lead to an electric shock. The board must be grounded separately, if the unit is supplied via power jack.

⚠ WARNING

Hot Plugging power supply is not supported.
Hot plugging might damage the board.

NOTICE

To protect the external power lines of peripheral devices make sure that

- ▶ the wires have the right diameter to withstand the maximum available current.
- ▶ to enclosure of the peripheral device fulfills the fire-protecting conditions of IEC/EN 60950.

6.8. Internal Power Connector (Vin Int., J4)

Figure 13: Internal Power Connector




Table 16: Internal Power Connector

Header	Pin	Signal	Description
1	+5V	+5V power input	PWR
2	+5V	+5V power input	PWR
3	GND	Power Ground	PWR
4	GND	Power Ground	PWR

Maximum allowed current on each pin is 3A.

6.9. Front Panel (FP) internal (J21)

Figure 14: FP Connector




Table 17: FP Connection

Pin	Description	Pin	Description
1	Ext_Reset	2	Ext_PWRBTN
3	GND	4	GND
5	Ext_SPKR	6	Ext_V_5V0_S0
7	Ext_3V3_S5_P7	8	Ext_V_3V3_S5_P8
9	Ext_SATA_LED#	10	Ext_SUS_LED

6.10. USB internal (J7, J8)

Figure 15: USB Internal Connector




Table 18: USB Internal Connection

Pin	Description	Pin	Description
1	GND	2	USBn+
3	USBn-	4	5 V/SB 5 V

6.11. SBC Connector (GPIO and Ext. Battery) (internal, J13))

Figure 16: SBC Connector




Table 19: SPI Internal Connection

Pin	Description	Pin	Description
1	V_3V3_S5	2	FGPIO0
3	FGPIO1	4	FGPIO2
5	FGPIO3	6	FGPIO4
7	FGPIO5	8	FGPIO6
9	FGPIO7	10	GND
11	GND	12	EXT_BAT

6.12. Jumper Load BIOS Default and Clear CMOS (J15)

Figure 17: CMOS Internal Connector




Table 20: CMOS Internal Connection

Pin	Description
1	RTC_TEST#
2	GND
3	DIS_SECCMOS



Function:

Pin 1-2: Clear CMOS

Pin 1-X: Default

Pin 2-3: Load BIOS Default

6.13. Jumper Always ON (J16)

Figure 18: Always ON




Table 21: Always ON Internal Connection

Pin	Description
1	GND
2	AUTOSTART#
3	NC



Function:

Pin1-2: Always ON

Pin2-3: Default Position

6.14. LVDS (internal, J19)

Figure 19: LVDS Connector




Table 22: LVDS Pin Assignment

Pin	Description	Pin	Description
1	5 V	2	5 V
3	5 V	4	5 V
5	5 V	6	GND
7	5 V	8	GND
9	V_LVDS	10	V_LVDS
11	LVDS_DDC_CLK	12	LVDS_DDC_DATA
13	LVDS_EDP_BKLTCTL	14	LVDS_EDP_VDD_EN
15	LVDS_BKLT_EN_OUT	16	GND
17	LVDS_A_DATA0-	18	LVDS_A_DATA_A0+
19	LVDS_A_DATA1-	20	LVDS_A_DATA_A1+
21	LVDS_A_DATA2-	22	LVDS_A_DATA_A2+
23	LVDS_A_CLK-	24	LVDS_A_CLK+
25	LVDS_A_DATA3-	26	LVDS_A_DATA3+
27	GND	28	GND
29	LVDS_B_DATA0-	30	LVDS_B_DATA_A0+
31	LVDS_B_DATA1-	32	LVDS_B_DATA1+
33	LVDS_B_DATA2-	34	LVDS_B_DATA2+
35	LVDS_B_CLK-	36	LVDS_B_CLK+
37	LVDS_B_DATA3-	38	LVDS_B_DATA3+
39	GND	40	GND

6.15. SATA (Serial ATA) Disk Interfaces (internal, J9)

Figure 20: SATA Connector




Table 23: Pin Assignment

Pin	Signal	Type
1	GND	PWR
2	SATA* TX+	
3	SATA* TX-	
4	GND	PWR
5	SATA* RX-	
6	SATA* RX+	
7	GND	PWR

Table 24: Signal Description

Signal	Description
SATA0 RX+ / RX-	Host transmitter differential signal pair
SATA0 TX+ / TX-	Host receiver differential signal pair

Figure 21: Available Cable Kit



6.16. Display Port

The two external Display Port 1.2 at rear I/O space are supporting Active/Passive HDMI 1.4a and DVI adapters.

Figure 22: Display Port




Table 25: Display Port

Pin	Signal	Description
1	ML_Lane 0 (p)	Lane 0 (positive)
2	GND	Ground
3	ML_Lane 0 (n)	Lane 0 (negative)
4	ML_Lane 1 (p)	Lane 1 (positive)
5	GND	Ground
6	ML_Lane 1 (n)	Lane 1 (negative)
7	ML_Lane 2 (p)	Lane 2 (positive)
8	GND	Ground
9	ML_Lane 2 (n)	Lane 2 (negative)
10	ML_Lane 3 (p)	Lane 3 (positive)
11	GND	Ground
12	ML_Lane 3 (n)	Lane 3 (negative)
13	CONFIG1	connected to Ground ¹⁾
14	CONFIG2	Connected to Ground ¹⁾
15	AUX CH (p)	Auxiliary Channel (positive)
16	GND	Ground
17	AUX CH (n)	Auxiliary Channel (negative)
18	Hot Plug	Hot Plug Detect
19	Return	Return for Power
20	DP_PWR	Power for connector (3.3 V 500 mA)

6.17. Slot Connector (mPCIe/mSATA) (J10)

NOTICE

The Slot connector has two functions: mSATA or miniPCIe. The Slot connector detects the mounted card technology with autosensing. So there is no need for further configuration.

Figure 23: Slot Connector (mPCIe)




Table 26: Pin Assignment mPCIe

Pin	Signal	Type
1	WAKE#	
2	+3V3	PWR
3	NC	NC
4	GND	PWR
5	NC	NC
6	+1.5V	PWR
7	CLKREQ#	
8	UIM_PWR	PWR
9	GND	PWR
10	UIM_DATA	NC
11	PCIE_mini CLK#	
12	UIM_CLK	NC
13	PCIE_mini CLK	
14	UIM_RESET	NC
15	GND	PWR
16	UIM_VPP	NC
17	UIM_IC_DM	NC
18	GND	PWR
19	UIM_IC_DP	
20	W_Disable#	
21	GND	PWR
22	RST#	
23	PCIE_RX-/SATA_RX-	
24	+3V3	PWR
25	PCIE_RX+/SATA_RX+	
26	GND	PWR

Pin	Signal	Type
27	GND	PWR
28	+1.5 V	PWR
29	GND	PWR
30	SMB_CLK	
31	PCIE_TX-/SATA_TX-	
32	SMB_DATA	
33	PCIE_TX+/SATA_TX+	
34	GND	PWR
35	GND	PWR
36	USBhub_D1_N	IO
37	GND	PWR
38	USBhub_D1_P	IO
39	+3V3	PWR
40	GND	PWR
41	+3V3	PWR
42	NC	NC
43	SATA_DET5#	
44	NC	NC
45	NC	NC
46	NC	NC
47	NC	NC
48	+1.5 V	PWR
49	NC	NC
50	GND	PWR
51	NC	NC
52	+3V3	PWR

6.18. Serial COM (J20)

Figure 24: Serial COM




Table 27: Pin Assignment Serial COM

Pin	Signal
1	RS232_TXD
2	RS232_RXD
3	RS232_RTS#
4	RS232_CTS#
5	GND

6.19. Front Panel Audio Connector (J22)

Figure 25: Audio Connector




Table 28: Pin Assignment Audio Connector

Pin	Signal
1	LINE_OUT_R_HEADER
2	GND
3	LINE_OUT_L_HEADER
4	LINE_IN_R_HEADER
5	MIC_IN_HEADER
6	LINE_IN_L_HEADER

7/ uEFI BIOS

7.1. Starting the uEFI BIOS

The pITX-APL is provided with a Kontron-customized, pre-installed and configured version of American Megatrends, Inc. (AMI). It is based on the Unified Extensible Firmware Interface (uEFI) specification and the Intel® Platform Innovation Framework for EFI. This uEFI BIOS provides a variety of new and enhanced functions specifically tailored to the hardware features of the pITX-APL.



The BIOS version covered in this document might not be the latest version. The latest version might have certain differences to the BIOS options and features described in this chapter.

The uEFI BIOS comes with a Setup program which provides quick and easy access to the individual function settings for control or modification of the uEFI BIOS configuration. The Setup program allows the accessing of various menus which provide functions or access to sub-menus with more specific functions of their own.

To start the uEFI BIOS Setup program, follow the steps below:

1. Power on the board.
2. Wait until the first characters appear on the screen (POST messages or splash screen).
3. Press the key.
4. If the uEFI BIOS is password-protected, a request for password will appear. Enter either the User Password or the Supervisor Password (see Security menu), press <RETURN>, and proceed with step 5.
5. A Setup menu will appear.

The pITX-APL uEFI BIOS Setup program uses a hot key-based navigation system. A hot key legend bar is located on the bottom of the Setup screens.

The following table provides information concerning the usage of these hot keys.

Table 29: Navigation Hot Keys Available in the Legend Bar

Hotkeys	Description
<F1>	The <F1> key is used to invoke the General Help window.
<->	The <Minus> key is used to select the next lower value within a field.
<+>	The <Plus> key is used to select the next higher value within a field.
<F4>	The <F4> key is used to Exit saving Changes.
<F3>	The <F3> key is used to load Optimized Defaults.
<→> or <←>	The <Left/Right> arrows are used to select major Setup menus on the menu bar. For example: Main screen, Advanced screen, Security screen, etc.
<↑> or <↓>	The <Up/Down> arrows are used to select fields in the current menu. For example a Setup function or a sub-screen.
<ESC>	The <ESC> key is used to exit a Setup menu.
<ENTER>	The <ENTER> key is used to execute a command or select a submenu.

7.2. Setup Menus

The Setup utility features a selection bar at the top of the screen that lists the available menus:

1. Main
2. Advanced
3. Chipset
4. Security
5. Boot
6. Save & Exit


The currently active menu and the currently active uEFI BIOS Setup item are highlighted in white. Use the left and right arrow keys to select the Setup menus.

Each Setup menu provides two main frames. The left frame displays all available functions. Configurable functions are displayed in blue. Functions displayed in black provide information about the status or the operational configuration. The right frame displays a Help window providing an explanation of the respective function.

7.2.1. Main Setup Menu

On entering the uEFI BIOS, the Setup program displays the Main Setup menu. This screen lists basic system and board information.

Figure 26: Main Setup Menu Initial Screen



The following table shows Main sub-screens and functions, and describes the content. Default settings are in **bold**.

Table 30: Main Setup Menu Sub-screens

Sub-Screen	Function	Second level Sub-Screen / Description
BIOS Information	Read only field	
	<i>Displays BIOS Information</i>	
	Board Vendor, BIOS Version, Build Date and Time, Access Level	
Board Information	Read only field	
	<i>Displays Board Information</i>	
	Manufacturer, Product Name, PCB Version, Serial Number, Part Number, Boot Count	
On-board LAN Information	Read only field	
	<i>Displays LAN MAC Address</i>	
CPU Information	Read only field	
	<i>Displays CPU Information</i>	
Memory Information	Read only field	
	<i>Displays Memory Information</i>	
Platform firmware Information	Read only field	
	<i>Displays Platform firmware Information</i>	
System Date>	Sets the system date	
	[mm/dd/yyyy]	
System Time>	Sets the system time	
	[hh:mm:ss]	


7.2.2. Advanced Setup Menu

The Advanced Setup menu provides sub-screens and second level sub-screens with functions, for advanced configuration and Kontron specific configurations.

NOTICE

Setting items, on this screen, to incorrect values may cause system malfunctions.

Figure 27: Advanced Setup Menu Initial Screen



The following table shows the Advanced sub-screens and functions and describes the content. Default settings are in **bold** and some functions include additional information. The function / submenu in *italic* indicate either status display or submenu string that cannot be selected. The underlined statement indicates the condition for the availability of the second-level submenu in reference to submenu.

Table 31: Advanced Setup menu Sub-screens and Functions

Sub-Screen	Function	Second level Sub-Screen / Description
Driver Health	Intel® PRO/1000 7.0.06 PCI-E	
Trusted Computing	TPM20 Device Status, Vendor and Firmware Version. Security Device Support [Enable]	<u>When set to Enable:</u> Active PCR banks Available PCR banks
		SHA-1 PCR Bank [Enabled]
		SHA256 PCR Bank [Enabled]
		Pending operation [None]
		Platform Hierarchy [Enabled]
		Storage Hierarchy [Enabled]
		Endorsement Hierarchy [Enabled]
		TPM2.0 UEFI Spec Version [TCG_2]
		Physical Presence Spec Version [1.3]
		TPM 20 InterfaceType [TIS]
		Device Select [Auto]
ACPI Settings	Enable ACPI Auto Configuration (Disabled)	<u>When set to Disable:</u> Enable Hibernation [Enabled] ACPI Sleep State [S3 (Suspend to RAM)] Lock Legacy Resources [Disabled]
SMART Settings	SMART Self Test [Disabled]	
Serial Port Console Redirection	Console Redirection (COM0) > [Disabled]	<u>When set to Enabled:</u> COM# Console Redirection Settings [ANSI] Bits per second [115200] Data Bits [None] Stop Bits [1] Flow Control [None] VT-UTF8 Combo Key Support [Enabled] Recorder Mode [Disabled] Resolution 100x31 [Disabled] Legacy OS Redirection Resolution [80x24] Putty KeyPad [VT100] Redirection After BIOS POST [Always Enable]
	Legacy Console Redirection Settings >	Legacy Serial Redirection Port [COM0]
	Serial Port for Out-of-Band Management / Windows Emergency Management Services (EMS) Console Redirection > [Disabled]	<u>When set to Enabled:</u> Console Redirection Settings > Out-of-Band Mgmt Port [COM0] Terminal Type [VT-UTF8] Bits per second [115200] Flow Control [None] Data Bits [8]

Sub-Screen	Function	Second level Sub-Screen / Description
		Parity [None] Stop Bits [1]
CPU Configurati on	Turbo Mode [Enabled]	
	Intel Virtualization Technology [Enabled]	
	VT-d [Disabled]	
	Monitor Mwait [Disabled]	
AMI Graphic Output Control Policy	<i>Intel ® Graphics Controller</i> <i>Intel ® GOP Driver</i> Output select [DP1]	
PCI Subsystem Settings	<i>AMI PCI Driver Version</i> Above 4G Decoding [Disabled]	
	Hot-Plug Support [Enabled]	
Network Stack Configurati on	Network Stack [Disabled]	
CSM Configurati on	CSM Support [Enabled]	<u>When set to Enabled:</u> <i>CSM16 Module Version 07.79</i> GateA20 Active [Upon Request] INT19 Trap Response [Immediate] Boot option filter [UEFI and Legacy] <i>Option ROM execution</i> Network [UEFI] Storage [UEFI] Video [UEFI] Other PCI devices [UEFI]
NVMe Configurati on	NVME controller and Drive information	
SDIO Configurati on	SDIO Access Mode [Auto] <i>Mass Storage Devices:</i>	
USB Configurati on	Legacy USB Support [Enabled]	
	XHCI Hand-off [Enabled]	
	USB Mass Storage Driver Support [Enabled]	
	USB transfer time-out [20 sec]	
	Device reset time-out [20 sec]	
	Device power-up delay [Auto]	
Security Configurati on	TXE HMRFP0 [Disabled]	
	TXE EOP Message [Enabled]	

Sub-Screen	Function	Second level Sub-Screen / Description
LVDS Configuration	LVDS Flat Panel Display Support [Disabled]	<u>When set to Enabled:</u> Panel Type [Standard] Resolution [1024 x 768] Panel Color Depth [24-Bit VESA] Panel Voltage [3.3V] Channel [Dual] Bus Swapping [Normal] Clock Frequency Center Spread [Disabled] Differential Output Swing Level [300 mV] Backlight [Enable] Backlight Signal Inversion [Disable] Backlight PWM Frequency [200 Hz] Brightness Level [80%]
Hardware Monitor	<i>Hardware Monitoring:</i> CPU DTS Temperature (CPU MSR) PCB Temperature (TD1) NCT7802Y Temperature (LTD) LM75B Temperature (I2C0) NCT7802Y Voltage (VCC) RTC Voltage (VCORE) DDR Voltage (VSENS2) Input Voltage (VSENS3)	
	<i>CPU Fan:</i> CPU Fan Pulse CPU Fan Control Mode [SMART FAN IV] Fan Trip Point Trip Point Speed	
CPLD Configuration	Serial Port 0 [Enabled]	<u>When set to Enabled:</u> Base Address [3E8] IRQ [10]
	GPIO IRQ [Disabled] I2C IRQ [Disabled]	
Watchdog	Auto-reload [Disabled]	
	Global Lock [Disabled]	
	Stage 1 mode [Disabled]	
Thermal	Automatic Thermal Reporting [Disabled]	<u>When set to Disabled:</u> Critical Trip Point [125 C] Passive Trip Point [95 C] Passive TC1 value 1 Passive TC2 value 5 Passive TSP value 10
System Component	OS Reset Select [Cold Reset]	
	Spread Spectrum Clocking Configuration	
	DDR SSC [Enable]	<u>When set to Enable:</u> DDR SSC Selection Table [-0.5%]

Sub-Screen	Function	Second level Sub-Screen / Description
	DDR SSC Bending Selection Table [0% (No Clock Bending)]	
	HighSpeed SerialIO SSC [Enable]	<u>When set to Enable:</u> HighSpeed SerialIO SSC Selection Table [-0.5%]
Debug Configurati on	Kernel Debugger Configuration Kernel Debugger Enable [Disabled]	
	APEI BERT Configuration APEI BERT [Enable]	
	ACPI Memory Debug Switch ACPI Memory Debug [Disable]	
	TXE Debug Option End of Post [Disable] Lock Directory [Disable]	
	PTT Debug Option Suppress PTT Commands [Disable]	
	TDO GPIO Pin Switch TDO GPIO Pin [Enable]	
	Max Memory 2G [Disable]	
	Persistent RAM Size [Disable]	
	OS DnX OS DnX focus entry [Disable]	
	Processor Trace Configuration Processor Trace memory allocation [Disable]	
	CSE Data Clear Option CSE Data Clear (Yes / No)	
	Option to clear Data region during IFWI Update Capsule Data Clear [Enable]	
	NPK Debug Configuration >	North Peak Enable [Auto] FW Trace Enable [Enable] FW Trace Destination [PTI] NPK Recovery Dump [Disable] Memory Region 0 Buffer Size [None] Memory Region 0 Buffer WrapAround [Wrap] Memory Region 1 Buffer Size [None] Memory Region 1 Buffer WrapAround [Wrap] PTI Mode [X4] PTI Training [Off] PTI Speed [Quarter Speed]

Sub-Screen	Function	Second level Sub-Screen / Description
		Punit Message Level [LEVEL LOW] PMC Message Level [LEVEL LOW]
RC ACPI Settings	Native PCIE Enable [Enable]	
	Native ASPM [Enable]	
RTD3 Settings	RTD3 Support [Disable]	

7.2.3. Chipset Setup Menu

The Chipset Setup menu provides sub-screens, second level and third level sub-screens with functions, for Intel Chipset configurations.

Figure 28: Chipset Setup Menu Initial Screen




Table 32: Chipset Setup menu Sub-screens and Functions

Sub-Screen	Function	Second level Sub-Screen / Description
North Bridge	Max TOLUD [2 GB]	
	PCIE VGA Workaround [Disable]	
South Bridge	Serial IRQ Mode [Continuous]	
	SMBus Support [Enabled]	


Sub-Screen	Function	Second level Sub-Screen / Description
	OS Selection [Windows 10 (Ver>=167)]	
	PCI Clock Run [Enable]	
	Real Time Option [RT Disable]	
Uncore Configuration	<i>GOP Configuration</i> GOP Driver [Enable] Intel Graphics Pei Display PEIM [Disable] GOP Brightness Level [140]	
	<i>IGD Configuration</i> Integrated Graphics Device [Enable] Primary Display [IGD] RC6 (Render Standby) [Disable] GTT Size [8MB] Aperture Size [256MB] DVMT Pre-Allocated [64M] DVMT Total Gfx Mem [256M] Cd Clock Frequency [624 MHz] GT PM Support [Enable] PAVP Enable [Enable]	
	<i>IGD – LCD Control</i> BIA [Auto] ALS Support [Enable] IGD Flat Panel [Auto] IGD Boot Type [Auto] Panel scaling [Auto] GMCH BLC Control [PWM-Inverted]	
South Cluster Configuration	HD-Audio Configuration >	HD-Audio Support [Enable]
		Low Power Sub System LPSS HSUART #3 Support (D24:F2) [Enable] LPSS SPI #1 Support (D25:F0) [Enable] LPSS IOSF PMCTL S0ix Enable [Enable]
	LPSS Configuration >	<i>PCI Express Configuration</i> PCI Express Clock Gating [Enable] Port8xh Decode [Disable] Peer Memory Write Enable [Disable] Compliance Mode [Disable] > PCIe #0 BDF[00:13:00] LAN 1 > PCIe #1 BDF[00:13:01] mPCIe When PCIE #X is enabled: PCIe #X BDF[XX:XX:XX] [Auto] ASPM [Disable] L1 Substates [L1.1 & L1.2] ACS [Enable] URR [Disable] FER [Disable] NFER [Disable] CER [Disable] CTO [Default Setting] SEFE [Disable] SENF [Disable] SECE [Disable] PME SCI [Enable] Hot Plug [Disable] PCIE Speed [Auto] Transmitter Half Swing [Disable] Extra Bus Reserved 0 Reserved Memory 10 Reserved I/O 4
	PCI Express Configuration >	

Sub-Screen	Function	Second level Sub-Screen / Description
		PCH PCIE LTR [Enable] Snoop Latency Override [Auto] Non Snoop Latency Override [Auto] PCIE LTR Lock [Disable] PCIE Selectable De-emphasis [Enable]
		SATA Drives Chipset-SATA Controller Configuration SATA Port 0 Port 0 [Enable] SATA Port 0 Hot Plug Capability [Disable] SATA Port 1 (mSATA) Port 0 [Enable] SATA Drives >
	SCC Configuration >	SCC SD Card Support (D27:F0) [Enable]
	USB Configuration >	USB Port Disable Override [Disable] XHCI Disable Compliance Mode [FALSE]
	Miscellaneous Configuration >	State After G3 [S0 State] Power Button Debounce Mode [Enable] Wake on LAN [Disable] BIOS Lock [Disable] RTC Lock [Enable] TCO Lock [Disable] DCI Enable (HDCIEN) [Disable] DCI Auto Detect Enable [Enable] GPIO Lock [Disable]

7.2.4. Security Setup Menu

The Security Setup menu provides information about the passwords and functions for specifying the security settings. The passwords are case-sensitive.

Figure 29: Security Setup Menu Initial Screen



The following table shows Security sub-screens and functions.

Table 33: Security Setup Menu Functions

Function	Description
Setup Administrator Password User Password	Create / change password to enter Setup
HDD Security Configuration	Create / change password to allow access to Set, Modify and Clear HardDisk User and Master Passwords for Enabling Security.
Attempt Secure Boot [Disable]	Enable or Disable the Secure Boot support. Please also set Secure Boot Mode to "Standard" to install standard Microsoft Platform Key (PK).
Secure Boot Mode	Set Secure Boot Mode to "Standard" to boot standard Windows or Linux boot loader signed with Microsoft's platform key. Select "Customized" mode only if you have a custom OS with OS boot loader signed with your own platform key. Kontron provide services for Customized Secure Boot, visit Kontron SEC-Line home

Function	Description
	page https://www.kontron.com/products/solutions/security/sec-line.html for more information.
Key Management	Enables expert users to modify Secure Boot Policy Variables without full authentication.



If only the administrator's password is set, then only access to the setup is limited and is requested when entering the setup.

If the user's password is set, then the password is a power on password and must be entered to boot or enter setup. In the setup the user has restricted rights.

7.2.4.1. Remember the Password


It is highly recommended to keep a record of all passwords in a safe place. Forgotten passwords result in the user being locked out of the system.

If the system cannot be booted because the User Password or the Supervisor Password are not known, contact Kontron Support for further assistance.

7.2.5. Boot Setup Menu

The Boot Setup menu lists dynamically generated boot device priority order.

Figure 30: Boot Setup Menu Initial Screen



The following table shows Boot sub-screens and functions, and describes the content. Default settings are in **bold**.

Table 34: Boot Setup Menu Functions

Function	Description
<i>Boot Configuration</i> Setup Prompt Timeout 1 Bootup NumLock State [On] Quiet Boot [Enabled]	
<i>Boot Option Priorities</i> Boot Option #1 Boot Option #2 Boot Option #3 Boot Option #4 Fast Boot [Enable] SATA Support VGA Support USB Support	To set the system boot order. Use +/- keys to change option. When Fast Boot is Enabled, SATA, VGA, USB, PS2 support, devices initialization, Network Stack driver can be customized.

Function	Description
PS2 Support Network Stack Driver Support Redirection Support	
New Boot Option Policy	Controls the placement of newly detected UEFI boot options
Hard Drive BBS Priorities	Sets the placement of legacy boot options


7.2.6. Exit Setup Menu

The Save and Exit Setup menu provides functions for handling changes made to the uEFI BIOS settings and exiting the Setup program.



If system cannot boot or work properly due to incorrect setting, shorting Pin-1 and Pin-2 on J15 jumper will load the default setting of BIOS upon power cycle. Once safely booted with default setting, you may undo the jumper setting to save new changes on BIOS Setup Menu.

Figure 31: Save and Exit Setup Menu Initial Screen



The following table shows the Exit menu sub-screens and functions, and describes the content.

Table 35: Save and Exit Setup Menu Functions

Function	Description
<i>Save Options</i> Save Changes and Exit Discard Changes and Exit Save Changes and Reset Discard Changes and Reset <i>Default Options</i> Restore Defaults Save as User Defaults	

Function	Description
Restore User Defaults	
<i>Boot Override</i> UEFI: Built-in EFI Shell Launch EFI Shell from filesystem device	

7.3. The uEFI Shell

The Kontron uEFI BIOS features a built-in and enhanced version of the uEFI Shell. For a detailed description of the available standard shell scripting, refer to the EFI Shell User Guide. For a detailed description of the available standard shell commands, refer to the EFI Shell Command Manual. Both documents can be downloaded from the EFI and Framework Open Source Community homepage (<http://sourceforge.net/projects/efi-shell/files/documents/>).



Kontron uEFI BIOS does not provide all shell commands described in the EFI Shell Command Manual. If Secure Boot is enabled, the UEFI shell may not be able to be entered.

7.3.1. Basic Operation of the uEFI Shell

7.3.1.1. Entering the uEFI Shell

To enter the uEFI Shell, follow the steps below:

1. Power on the board.
2. Press the <F7> key (instead of) to display a choice of boot devices.
3. Choose 'UEFI: Built-in EFI Shell'.

```
EFI Shell version 2.50 [5.12]
Current running mode 1.1.2
Device mapping table
fs0      :Removable HardDisk - Alias hd18c0b blk0
          PciRoot(0x0)/Pci(0x15,0x0)/USB(0x2,0x0)/HD(1,MBR,0x0002B27D,0x3F,0x785BEC)
blk0     :Removable HardDisk - Alias hd18c0b fs0
          PciRoot(0x0)/Pci(0x15,0x0)/USB(0x2,0x0)/HD(1,MBR,0x0002B27D,0x3F,0x785BEC)
blk1     :Removable BlockDevice - Alias (null)
          PciRoot(0x0)/Pci(0x15,0x0)/USB(0x2,0x0)
```

Press the ESC key within 5 seconds to skip startup.nsh, and any other key to continue.

4. The output produced by the device-mapping table can vary depending on the board's configuration.
5. If the ESC key is pressed before the 5 second timeout elapses, the shell prompt is shown:

```
Shell>
```

7.3.1.2. Exiting the uEFI Shell

To exit the uEFI Shell, follow one of the steps below:

1. Use the **exit** uEFI Shell command to select the boot device, in the Boot menu, that the OS will boot from.
2. Reset the board using the **reset** uEFI Shell command.

7.4. uEFI Shell Scripting

7.4.1. Startup Scripting

If the ESC key is not pressed and the timeout has run out then the uEFI Shell tries to execute some startup scripts automatically. It searches for scripts and executes them in the following order:

1. Initially searches for Kontron flash-stored startup script.
2. If there is no Kontron flash-stored startup script present then the uEFI-specified **startup.nsh** script is used. This script must be located on the root of any of the attached FAT formatted disk drive.
3. If none of the startup scripts are present or the startup script terminates then the default boot order is continued.

7.4.2. Create a Startup Script

Startup scripts can be created using the uEFI Shell built-in editor `edit` or under any OS with a plain text editor of your choice. To create a startup shell script, simply save the script on the root of any FAT-formatted drive attached to the system.

7.4.3. Examples of Startup Scripts

7.4.3.1. Execute Shell Script on other Harddrive

This example (**startup.nsh**) executes the shell script named **bootme.nsh** located in the root of the first detected disc drive (**fs0**).

```
fs0:
bootme.nsh
```

7.5. Firmware Update

Firmware updates are typically delivered as a ZIP archive containing only the firmware images. The content of the archive with the directory structure must be copied onto a data storage device with FAT partition.

7.5.1. Updating Procedure

BIOS can be updated with the Intel tool `fpt64.efi` using the procedure below:

1. Copy these files to an USB stick.
 - ▶ `flash.nsh` or `flash_with_fpt.nsh` (if available)
 - ▶ `fpt.efi`
 - ▶ `fparts.txt`
 - ▶ `pITX_APL_BIOS_Ver_<xxx>.....bin` (where `xxx` stands for the version #)
2. Start the system into the uEFI shell (see chapter 7.3.1.1 "Entering the uEFI Shell").
3. Change to the drive representing the USB stick.

```
fsx: (x = 0,1,2,etc. represents the USB stick)
```

Change to the directory where you copied the flash tool.

```
cd <your directory>
```

4. Start `flash.nsh` or `flash_with_fpt.nsh` (if available)

OR type

```
fpt -y -f pITX APL BIOS Ver <xxx>.....bin
```

5. Wait until flashing is successful and then power cycle the board.



Do not switch off the power during the flash process!

List of Acronyms

DP	Display Port
DVI	Digital Video Interface
EDP	Embedded DisplayPort
EMI	Electromagnetic Interference
ESD	Electrostatic Discharge
FCBGA	Flip Chip Ball Grid Array
FWH	Firmware Hub
HDMI	High Definition Multimedia Interface
LPC	Low Pin Count
LVDS	Low Voltage Differential Signaling
MPCIE	Mini PCI Express
MSATA	Mini Serial ATA
PCBA	Printed Circuit Board Assembly
PEG	PCI Express Graphics
RTC	Real Time Clock
SATA	Serial ATA
SDVO	Serial Digital Video Out
SMBUS	System Management Bus
SOC	System on Chip
SPI	Serial Peripheral Interface
TPM	Trusted Platform Module
ULV	Ultra-low Voltage
USB	Universal Serial Bus



About Kontron

Kontron, a global leader in embedded computing technology and trusted advisor in Internet of Things (IoT), works closely with its customers, allowing them to focus on their core competencies by offering a complete and integrated portfolio of hardware, software and services designed to help them make the most of their applications.

With a significant percentage of employees in research and development, Kontron creates many of the standards that drive the world's embedded computing platforms; bringing to life numerous technologies and applications that touch millions of lives. The result is an accelerated time-to-market, reduced total-cost-of-ownership, product longevity and the best possible overall application with leading-edge, highest reliability embedded technology.

For more information, please visit: <http://www.kontron.com/>



Global Headquarters

Kontron S&T AG

Lise-Meitner-Str. 3-5
86156 Augsburg
Germany
Tel.: + 49 821 4086-0
Fax: + 49 821 4086-111
info@kontron.com